

**S&C ELECTRIC
 PME
 CROSS REFERENCE GUIDE**

S&C Manual PME (underground distribution switchgear)

Pad-mounted Style Switchgear

SPECIFICATION BULLETIN 665-31 DATED: FEBRUARY 20, 2012

Models PME 4, 5, 6, 9, 10, 11, 12

Most Requested

S & C Model	KV, Nom.	Fuse Type	S&C Cabinet Width	S&C Cabinet Depth	*	E-GLASS PAD-VAULT CAT.#	*	Pad-Vault Top Surface W x D	Pad-Vault Top Opening W x D	Pad-Vault Height Ht.
PME-4	14.4	SME-20	41"	52 3/4"	*	SG-5844	*	58" x 44"	48" x 33"	30"
	25	SME-20	46"	62 1/4"	*	SG-BP3500	*	52.5" x 70"	42.5" x 60"	31"
PME-5	14.4	SME-20	41"	66 3/4"	*	SG-7245	*	45" x 72"	33" x 60"	30"
	25	SME-20	46"	81 3/4"	*	SG-8646-MTO-1	*	46" x 86"	38" x 72"	32"
PME-6	14.4	SME-20	75"	66 3/4"	*	SG-7378	*	78" x 73.5"	60" x 55.5"	32"
	25	SME-20	84"	81 3/4"	*	SG-8590	*	90" x 85"	76" x 75"	32"
PME-9	14.4	SME-20	75"	66 3/4"	*	SG-7378	*	78" x 73.5"	60" x 55.5"	32"
	25	SME-20	84"	81 3/4"	*	SG-8590	*	90" X 85"	76" X 75"	32"
PME-10	14.4	-----	75"	72 3/4"	*	SG-7378	*	78" x 73.5"	60" x 55.5"	32"
	25	-----	84"	88 1/4"	*	SG-8590	*	85" X 90"	75" X 76"	32"
PME-11	14.4	SME-20	75"	72 3/4"	*	SG-7378	*	78" x 73.5"	60" x 55.5"	32"
	25	SME-20	84"	88 1/4"	*	SG-8590	*	85" X 90"	75" X 76"	32"
PME-12	14.4	SME-20	75"	66 3/4"	*	SG-7378	*	78" x 73.5"	60" x 55.5"	32"
	25	SME-20	84"	81 3/4"	*	SG-8590	*	90" X 85"	76" X 75"	32"